



The Foxgear ANUBI series consists of two different devices: the Ambient BOX (Blue) and the Modulation BOX (Pink). Based on the trusty FV-1 Digital processor used in many boutique pedals, including our award winning Rainbow, the Anubi boasts a super bright LCD display, visible in any light conditions, and a super easy-to-use interface:

- Stereo Engine (input & output)
- Midi interface to manage Presets and EXP.
- 16 Algorithms
- 128 Presets Available
- 16 Midi Programmable Channels
- LCD display
- Analog MIX
- Digital Programmable Mix
- 100% Analog Signal Path
- Class A buffered Bypass with Relay

The Anubi Box is the perfect addition to your pedalboard or your Amplifier's FX Loop as a master FX unit, Anubi is able to give you one of the widest choice of premium designed Algorithms both for Ambient (Reverb, Delays, Chorus) or Modulation (Chorus, Phaser, Tremolo, Leslie, Flanger) and even some together (Rev+Dly, Rev+Chorus, etc..). You can easily manage it by Midi pedalboard, or Midi Looper/Switcher To Change up to 128 Presets with 16 different Algorithms and also use Control Change to assign an expression pedal to modify each parameter like delay time, levels, speed, or pitch shifting to obtain a fully working Whammy effect.

## FUNCTIONS:



## TECH SPECS.

<b>Power In</b>	9 to 12VDC (negative TIP)
<b>Mono IN (L) Mono Out (L)</b>	(Can accept Mono input with Stereo Out)
<b>Consumption at 9V</b>	70mA
<b>Input Impedance</b>	<=1M Ohm
<b>Output Impedance</b>	<=10K Ohm
<b>Lunghezza (Length)</b>	90mm. (3,5")
<b>Larghezza (Width)</b>	127mm. (5")
<b>Altezza (Height)</b>	30mm. (1,2")
<b>Peso (Weight)</b>	0,2Kg. (0,4lbs)

## Terms of Warranty

**FOXGEAR** product warranty covers 5 years from date of purchase. The warranty does not cover damage caused by accident, misuse and / or neglect, failure to comply with the instruction manual, repair and attempted repair by personnel not authorized by **FOXGEAR LLC**, any damage caused during transport and delivery, (claims must be presented to the carrier); damage to any product that has been altered or on which it has been removed, defaced or altered serial number; damage caused by faulty connections or connections to equipment failures and/or defective power cables. Responsibility of **FOXGEAR LLC** for any defective product is limited to repair or replacement of the product at our discretion. The **FOXGEAR LLC** not be liable for damages resulting from loss of use of the product, lost time operation interrupted by non-use of the product, loss of business or any other damages or incidental, consequential or otherwise; damage in transit or damage caused by inadequate packaging or of poor quality.

**Assistance:** Please contact us for information on how, where and when to ship the product after the return has been Authorized by **FOXGEAR LLC**. The repaired goods should be packed carefully and we recommend not include any accessories such as cables, effects, manuals, etc. ... Please attach a copy of the original receipt of purchase (invoice or receipt) together with a problem description and your personal details.

**THE WARRANTY IS NOT VALID WITHOUT A COPY OF YOUR RECEIPT OF SALE CERTIFYING THE DATE OF PURCHASE.**

Foxgear pedals are designed in Italy and proudly handmade in our own factory in PRC.

# ANUBI

THE MODULATION BOX



FOXGEAR LLC  
2011 Westley Ct, Safety Harbor,  
34695 Florida - USA  
support@foxgeardistribution.com



Scrolling the EDIT knob, you can set the different Algorithms and by pushing the Edit knob, you can access to the menu to modify all the parameters and values. Then you can push and Hold EDIT and push the Jog Shuttle to Save all the parameters to the selected preset. Very Easy! The Signal path is 100% analog and with Audio capacitors (no SMD) in the Audio Path, so the quality and dynamics are intact and superb.

The Main MIX set the general Analog MIX of the pedal over the Clean signal that always passes thru the pedal without being digitally converted to preserve the quality.

An additional digital mix is present in all the presets, which lets you modify and recall/save it to the desired level, from 100% WET, to the complete Bypass of the whole pedal.

**- PRESETS SAVING PROCEDURE:**

Push and hold EDIT and then push the Jog Shuttle.

**- MIDI CHANNEL PROCEDURE:**

By Keeping the EDIT control pushed for more than 3sec. you access to the MIDI menu, where you can select the Midi Channel from 1 to 16. Just select and wait until autosaving and exit.

ANUBI MODULATION BOX - ALGORITHMS/CONTROLS LIST:			
ALGORITHM NAME:	POT #1	POT #2	POT #3
1) ROOM CHORUS (Reverb + Chorus)	1) RVB= Reverb Level	1) INT= Mod Depth	1) EQ= Tone Filter
2) VIBE CHORUS (Vintage Vibe Chorus)	2) SPD= Chorus Speed	2) MOD= Modulation Type	2) INT= Mod Depth
3) CHORUS A	3) SPD= Chorus Speed	3) MOD= Modulation Type	3) INT= Mod Depth
4) CHORUS B	4) SPD= Chorus Speed	4) MOD= Modulation Type	4) INT= Mod Depth
5) CHORUS C	5) SPD= Chorus Speed	5) MOD= Modulation Type	5) INT= Mod Depth
6) PHASEREV ( Phaser + Reverb)	6) RVB= Reverb Level	6) SPD= Phaser Speed	6) INT= Mod Depth
7) STEREOPHASE (Stereo Phaser)	7) SPD= Phaser Speed	7) INT= Mod Depth	7) EQ= Tone Filter
8) ECHORUS (Echo + Chorus)	8) SPD= Chorus Speed	8) DTM= Delay Time	8) FBK= Delay Feedback
9) LESLIEVERB A (Rotary + Reverb)	9) RVB= Reverb Level	9) MOD= Modulation Type	9) SPD= Rotary Speed
10) LESLIEVERB B (Rotary + Reverb)	10) RVB= Reverb Level	10) EQ= Tone Filter	10) SPD= Rotary Speed
11) VIBERB (Vibe + Reverb)	11) RVB= Reverb Level	11) SPD= Vibe Speed	11) INT= Mod Depth
12) AUTOWAHVERB (AutoWha + Reverb)	12) RVB= Reverb Level	12) EQ= Tone Filter	12) INT= Intensity
13) WAMMER (Pitch Shifting/Octaver)	13) EXP= Pitch Transposer	13) OCT= Selector (see list)	13) -
14) POLYPITCH (Multi Pitch Options)	14) OCT= Selector (see list)	14) LEV= FX level	14) MIX= Octave Mix
15) TREMOVERB (Tremolo + Reverb)	15) RVB= Reverb Level	15) SPD= Phaser Speed	15) INT= Mod Depth
16) VINTPHASER (Classic Phaser)	16) SPD= Phaser Speed	16) INT= Mod Depth	16) EQ= Tone Filter